



EARLY HONDA WIRING COLORS

Wire Color		Used For	From	To
Black*		a. Switched Hot	a. Ignition Switch	a. Fuses
Black*		b. Switched Hot	b. Ignition Switch	b. Handlebar Switch
Black*		c. Switched Hot	c. Ignition Switch	c. Starter Switch
Black*		d. Battery Voltage Sense Lead	d. Ignition Switch	d. Voltage Regulator
Black / Brown		Fused Hot: Neutral Light	Fuse Box	Neutral Light
Black / Brown		Oil Light		Oil Light
Black / Red		Fused Hot (Headlight)	Fuse Box	Starter Switch
Black / White		Ignition System Hot	Ignition Handlebar Switch	Coils and T.P.I. Box
Blue / White		Switched Hot	Starter Switch	Dimmer Switch
Brown		Taillight	Brown / White (Ignition Switch)	Brown
Brown / Black		Fused Hot: Running Lights	Fuse Box	Brown / White Lead
Brown / Black		Meter Lights		
Brown / White		Running Lights	Brown / White	Turn Signal Switch
Brown / White		Meter Lights	Brown / White	Meters
Brown / White		Taillight	Brown / White	Ignition Switch
Green		Ground	Load	Ground
Green / Red		Starter Safety Circuit	Starter Relay to Diode to Clutch Switch	
Green / Yellow		Brake Light	Switch	Lamp
Grey		Hot Turn Signal	Meter Relay	Turn Signal Switch
Light Green		Horn Circuit	Horn	Horn Switch
Light Green / Red		Neutral Circuit	Bulb	Neutral Switch
Orange and Light blue		Switched Hot: Turn Signal	Turn Signal Switch	Turn Signal Bulb
Orange / White and Light Blue / White		Front Running Lights	Turn Signal Switch	Brown
Red*		Hot	Battery	Ignition Switch
Red / White		Charging Lead	Rectifier	Battery
White		Switched Hot: Lo	Dimmer Switch	Headlight
Blue		Switched Hot: Hi		
White / Green		Fused Hot: Turn Signal	Fuse Box	Turn Signal Relay
White / Green		Horn	Fuse Box	Horn
White / Green		Brake Light	Fuse Box	Brake Light Switches
Yellow		Charging System	Stator	Rectifier
Yellow and Blue		Ignition System	Coil	T.P.I. Box
Yellow / Red		Starter Circuit	Starter Switch	Starter Relay



DLVCCOASTALCYCLES.COM